

Current/Previous/Beta Releases

Update/downgrade Batocera

Most of the time you have two versions of the Batocera distribution available:

- **Stable:** most stable version, recommended for most users.
- **Beta:** bleeding-edge version, sometimes alpha or pre-alpha internal build. Stability is usually not an issue, but particular things can often be broken in this version.

From v5.27 onwards, you can switch what branch you're on by going to **Main Menu > Updates & Downloads > Update Type**.

You can also do the same by editing the appropriate line in `/userdata/system/batocera.conf/`:

```
updates.type=beta
```

Upon reboot, you'll be able to update your Batocera to the latest version of the type you've selected.

If you are on Batocera 5.25 or later, you can also check the latest version available from the command line with:

```
batocera-check-update
```

And if you want to check on the latest beta version, with its build date, you can type:

```
batocera-check-update beta
```

To update to that checked version, use:

```
batocera-upgrade
```

If you ever want to upgrade to a specific version, or the current checker is broken for whatever reason, you can use `batocera-upgrade [url of the build folder containing the version you want]`. For example:

```
batocera-upgrade https://mirrors.o2switch.fr/batocera/x86_64/stable/last/
```

Alternatively, you can also [upgrade manually](#).



You can see a short list of the most recently updated beta builds [on this page](#)!

Current builds

Device	URL	Torrent
PC 64-bit (most current computers)	https://mirrors.o2switch.fr/batocera/x86_64/stable/last/	
PC 32-bit (older computers)	https://mirrors.o2switch.fr/batocera/x86/stable/last/	
Raspberry Pi Zero and 1 (A/A+/B/B+, GPi case)	https://mirrors.o2switch.fr/batocera/rpi1/stable/last/	
Raspberry Pi 2	https://mirrors.o2switch.fr/batocera/rpi2/stable/last/	
Raspberry Pi 3 (A+/B/B+)	https://mirrors.o2switch.fr/batocera/rpi3/stable/last/	
Raspberry Pi 4 and Pi 400	https://mirrors.o2switch.fr/batocera/rpi464/stable/last/	
Odroid XU4	https://mirrors.o2switch.fr/batocera/odroidxu4/stable/last/	
Odroid C2	https://mirrors.o2switch.fr/batocera/odroidc2/stable/last/	
Odroid C4	https://mirrors.o2switch.fr/batocera/odroidc4/stable/last/	
Odroid N2 and N2+	https://mirrors.o2switch.fr/batocera/odroidn2/stable/last/	
Odroid Go Advance and variants	https://mirrors.o2switch.fr/batocera/odroidgoa/stable/last/	
s905 and variants	https://mirrors.o2switch.fr/batocera/s905/stable/last/	
s905gen3 and variants	https://mirrors.o2switch.fr/batocera/s905gen3/stable/last/	
Rockpro 64	https://mirrors.o2switch.fr/batocera/rockpro64/stable/last/	
Tinkerboard	https://mirrors.o2switch.fr/batocera/tinkerboard/stable/last/	
Miqi	https://mirrors.o2switch.fr/batocera/miqi/stable/last/	
Khadas Vim3	https://mirrors.o2switch.fr/batocera/vim3/stable/last/	
Libretech H5	https://mirrors.o2switch.fr/batocera/libretech-h5/stable/last/	

Sometimes a build for a particular device will stay on an older version of Batocera, this might be due to severe bugs affecting only that build for that device that couldn't be resolved in time for the major release. These are usually fixed by the next version.

Torrents are available but only the most popular platforms are updated. Always check the above list for the latest stable version. [Here's a link to the torrents page.](#)

Older releases

All the previous **stable** Batocera releases are kept and available for download from the following URLs. They are ordered by dates of releases:

Device	URL
PC 64-bit (most current computers)	https://mirrors.o2switch.fr/batocera/x86_64/stable/last/archives/
PC 32-bit (older computers)	https://mirrors.o2switch.fr/batocera/x86/stable/last/archives/
Raspberry Pi Zero and 1 (A/A+/B/B+, GPi case)	https://mirrors.o2switch.fr/batocera/rpi1/stable/last/archives/
Raspberry Pi 2	https://mirrors.o2switch.fr/batocera/rpi2/stable/last/archives/
Raspberry Pi 3 (A+/B/B+)	https://mirrors.o2switch.fr/batocera/rpi3/stable/last/archives/
Raspberry Pi 4 and Pi 400 64-bit	https://mirrors.o2switch.fr/batocera/rpi464/stable/last/archives/
Raspberry Pi 4 32-bit	https://mirrors.o2switch.fr/batocera/rpi4/stable/last/archives/

Device	URL
Odroid XU4	https://mirrors.o2switch.fr/batocera/odroidxu4/stable/last/archives/
Odroid C2	https://mirrors.o2switch.fr/batocera/odroidc2/stable/last/archives/
Odroid C4	https://mirrors.o2switch.fr/batocera/odroidc4/stable/last/archives/
Odroid N2 and N2+	https://mirrors.o2switch.fr/batocera/odroidn2/stable/last/archives/
Odroid Go Advance and variants	https://mirrors.o2switch.fr/batocera/odroidgoa/stable/last/archives/
s905 and variants	https://mirrors.o2switch.fr/batocera/s905/stable/last/archives/
s905gen3 and variants	https://mirrors.o2switch.fr/batocera/s905gen3/stable/last/archives/
Rockpro 64	https://mirrors.o2switch.fr/batocera/rockpro64/stable/last/archives/
Tinkerboard	https://mirrors.o2switch.fr/batocera/tinkerboard/stable/last/archives/
Miqi	https://mirrors.o2switch.fr/batocera/miqi/stable/last/archives/
Khadas Vim3	https://mirrors.o2switch.fr/batocera/vim3/stable/last/archives/
Libretech H5	https://mirrors.o2switch.fr/batocera/libretech-h5/stable/last/archives/

Beta releases

For **beta** and **pre-release** versions, only x86_64 and RPi3 builds are generated on a regular basis (they're the most commonly used architectures). You can ask to have a beta build for another architecture on our Discord server.

Beta versions can be downloaded from:

- Beta PC 64-bit (most current computers) https://mirrors.o2switch.fr/batocera/x86_64/beta/last/
- Beta Raspberry Pi 3 (A+/B/B+) <https://mirrors.o2switch.fr/batocera/rpi3/beta/last/>

In case the host goes down

You can use the internal upgrade URLs that Batocera uses instead. Just replace <https://mirrors.o2switch.fr/batocera/> with <https://updates.batocera.org/>. This server only has the current and beta releases, however.

Alternatively, you could check to see if any other users are currently seeding the image via the torrent magnet link.

From: <https://www.wiki.batocera.org/> - **Batocera.linux** - Wiki

Permanent link: https://www.wiki.batocera.org/current_and_previous_releases?rev=1635148382

Last update: **2021/10/25 07:53**

