

# Atari 800

The Atari 800 is a computer developed by Atari. It was released in 1979.



The current emulation of the Atari 800 based family of computers is not complete or fail safe. This wiki article only gives basic instructions so you can run some popular games. The full technical background on these issues can be found in this article: [Atari 8-Bit Guide \(Raph Koster\)](#). The script mentioned in these pages is **not** integrated into Batocera yet, so you are stuck with the manual fixes until then.

This system scrapes metadata for the "atari800" group and loads the atari800 set from the currently selected theme, if available.

## Quick reference

- **Emulator:** [RetroArch](#)
- **Core:** [libretro: atari800](#)
- **Folder:** /userdata/roms/atari800
- **Accepted ROM formats:** .rom, .xfd, .atr, .atx, .cdm, .cas, .car, .bin, .a52, .xex, .zip, .7z

## BIOS

No Atari 800 emulator in Batocera needs a BIOS file to run.

There are subtle differences in machine type between the different Atari Computers, including different version of the OS (BIOS). Some games will crash unless you manually select a different BIOS.



This is conflicting information, which is correct?

## ROMs

Place your Atari 800 ROMs in /userdata/roms/atari800.




Multi-Disk games can only be used with an internal menu of the emulator. Playlists and RetroArch features for these games are not supported.

# Emulators

## RetroArch

[RetroArch](#) (formerly SSNES), is a ubiquitous frontend that can run multiple “cores”, which are essentially the emulators themselves. The most common cores use the [libretro](#) API, so that's why cores run in RetroArch in Batocera are referred to as “libretro: (core name)”. RetroArch aims to unify the feature set of all libretro cores and offer a universal, familiar interface independent of platform.

### RetroArch configuration

RetroArch offers a **Quick Menu** accessed by pressing [HOTKEY] +  which can be used to alter various things like [RetroArch and core options](#), and [controller mapping](#). Most RetroArch related settings can be altered from Batocera's EmulationStation.

Standardized features available to all libretro cores: `atari800.videomode`, `atari800.ratio`, `atari800.smooth`, `atari800.shaders`, `atari800.pixel_perfect`, `atari800.decoration`, `atari800.game_translation`

ES setting name batocera.conf_key	Description ⇒ ES option key_value
<b>Settings that apply to all cores of this emulator</b>	
<b>GRAPHICS API</b> <code>atari800.gfxbackend</code>	Choose which graphics API library to use. Vulkan is better, when supported. ⇒ OpenGL <code>opengl</code> , Vulkan <code>vulkan</code> .
<b>AUDIO LATENCY</b> <code>atari800.audio_latency</code>	In milliseconds. Can reduce crackling/cutting out. ⇒ 256 256, 192 192, 128 128, 64 64, 32 32, 16 16, 8 8.
<b>THREADED VIDEO</b> <code>atari800.video_threaded</code>	Improves performance at the cost of latency and more video stuttering. Use only if full speed cannot be obtained otherwise. ⇒ On <code>true</code> , Off <code>false</code> .

### libretro: atari800

A [libretro port](#) of [Atari800](#). Originally written by David Firth in 1995 and released under the GPL.

### libretro: atari800 configuration

ES setting name batocera.conf_key	Description ⇒ ES option key_value
<b>Settings specific to atari800</b>	

ES setting name batocera.conf_key	Description ⇒ ES option key_value
<b>ATARI SYSTEM</b> atari800.atari800_system	Choose what Atari System to emulate ⇒ 400/600XL/800 (48K) (OS B) 400/800 (OS B), 800XL/1200XL/XEGS (64K) 800XL (64K), 130XE (128K) 130XE (128K), Modern XL/XE (320K CS) Modern XL/XE (320K CS), Modern XL/XE (576K) Modern XL/XE (576K), Modern XL/XE (1088K) Modern XL/XE (1088K).
<b>VIDEO STANDARD</b> atari800.atari800_ntscpal	Switch frequency and resolution by region ⇒ NTSC NTSC, PAL PAL.
<b>SIO ACCELERATION</b> atari800.atari800_sioaccel	Speeds up file loading (a few games will not load) ⇒ Off disabled, On enabled.
<b>HI-RES ARTIFACTING</b> atari800.atari800_artifacting	Artificial color filters to mimic actual hardware ⇒ Off disabled, On enabled.
<b>INTERNAL RESOLUTION</b> atari800.atari800_resolution	Enables alternate resolutions for some games ⇒ 336×240 336×240, 320×240 320×240, 384×240 384×240, 384×272 384×272, 384×288 384×288, 400×300 400×300.
<b>Settings specific to atari5200</b>	
<b>JOYSTICK HACK (FOR ROBOTRON)</b> atari5200.atari800_opt2	Treats the second analog stick as joystick 2 ⇒ Off disabled, On enabled.

## Controls

Analogue joysticks are supported only via hardcoded mouse inputs (bypassing RetroPad and default controls). The analog sticks of gamepads are NOT supported. This makes some games unplayable unless you connect a mouse.



Sure that it's not possible to [remap](#) them?

Here are the default Atari 800's controls shown on a [Batocera Retropad](#):



## Troubleshooting

### My game is black and white!

Many (US) games look wrong because they use specific video artifacts to generate colors on NTSC TVs but look black and white in emulation, unless you set specific parameters.





What parameters?

## Game is not booting

Most ROM sets are in a format that requires one additional input at the start of a ROM. Sometimes the selection screen is not visible making it look like the emulator crashed.



So what buttons are common to try to get out of this?

## Further troubleshooting

For further troubleshooting, refer to the [generic support pages](#).

From:

<https://www.wiki.batocera.org/> - **Batocera.linux - Wiki**

Permanent link:

<https://www.wiki.batocera.org/systems:atari800?rev=1638928334>

Last update: **2021/12/08 01:52**

